

# CRHONOMETER with BCD OUTPUTS.



The CD-16 module allows standard functions of a chronometer as "Start / Stop, Lapso / Reset", count up and count down, etc... with BCD data output. It accepts automatic count up / down and chronometer It could control CD-10, and CD-41 Cebek displays.

It includes protection against inversion polarity, Leds and acoustic indicators as wellas connection terminals

#### TECHNICAL CHARACTERISTICS.

Voltage	12 V. D.C.
Minimum Consumption	10 mA.
Maximum Consumption.	60 mA.
Chronometer time on Sacle No1.	From 0 till 99minutes.
Chronometer Time on Scale N°2.	From 0 sec. till 99 hours.
Signal level of BCD outputs	Voltage.
Maximum output load	5 A.
Protection against inversion polarity, (P.I.P.).	Yes.
Sizes.	96 x 95 x 30 mm.

## POWER SUPPLY AND INSTALLATION.

POWER SUPPLY. The CD-16 circuit had to be supplied by a 12 VDC power supply correctly filtered. We recommend you to use the FE-2power supply whichhas been developed to perfectly answer to the circuit needs. Install a fuse and a switch has it is indicated on the schedule. Bothare necessary for the module's protection as well as for your own safety, as it is required by the "CE" regulations. Connect the positive and the negative of the power supply to the respective positive and negative terminals of the module, indicated in the wiring map. The distance between the power supply and the module has to be as short as possible. Verify that the assembly is correct.

Note. Connections indicated as 230 VAC in the wiring map have to be connected to 110 VAC. in Americans countries. Cebek's Modules and/or transformers will be supplied with correspondingmodifications for their connection in the secountries.

### CONNECTION BETWEEN BCD OF THE CD-16 and BCD OF DISPLAYS.

CONNECTION BETWEEN BCD OF THE CD-16 and BCD OF DISPLAYS.


No order to visualise operations and data of the chronometer, you have to use displays with BCD inputs. With Cebek range you could find outseveral modules with BCD inputs composed by a single display (like CD-10 and CD-11) or by 4 display like the CD-41. All are completely compatible with the CD-16 module.

The CD-16 module offers BCD inputs: Units, tens, hundreds, thousands. Each input had to be connected to the corresponding display. If you don't proceed as mentioned, the digit displayed could be correctly read.

Each BCD output, itself, is composed by 4 data terminals: A, B, C and D. You haveto connect each terminal to its corresponding terminal on the display. The A terminaloff the CD-16 units has to beconnected with the A terminal of the displayunits; the B terminal of the CD-16 tens has to be connected with the A terminal of the displayunits; the B terminals CD-16 units has to beconnected with the A terminal of the display tens, and proceed like this with all terminals. Be careful on the assembly to be sure to correctly connect terminals A with A, B with B, etc.... See fig. 1. Then you will avoid any malfunction of the module.

If you don't use the same power supply for the CD-16 and Displays, you have to inter-connect their respective power supplies as well as negative terminals of the module of the module.

supplies as well as negative terminals of the module and displays. If you use the same power supply, to supply all modules, you don't need this connection.



**OUTPUT CONNECTION. LOAD.** The CD-16 output is controlled by a relay, and accept any device up to 5 A. The relay is not a component supplying voltage but its function is limited to accept or deny the voltage passage like a standard switch. For this reason, you have to supply the load throughthis component.


The relay has three output terminals: The normally open quiescent (NO), the normally closed quiescent (NC) and the common. Install it between the Common and the NOin accordance with the schedule "Output Connection. Load". For the inverse function you have to place the load between the NC and Common.

HOW TO CONNECT THE RELAY. The module relayoutput allows two operating modes. If you close the JP1 jumper, the relay will be activated and maintained in this state when you don't use the chronometer. At the opposite, and maintained in this state only when you use the

of the chronometer. See the Fig. 2.

If you leave open the JP Ijumper, (as it is originally supplied), the relay will be activated and maintained in this state onlywhen you use the chronometer. See the Fig. 2.

Fig. 2. Configuration of the Jp1 jumper.



## OPERATING MODE.

DO NOT FORGET. In several paragraphs of this instruction manual, it will be required to simultaneously press two buttons. The process that you have to follow to correctly do this operation, and to not confuse the module, is: Firstly you have to press on thefirst indicated button and then, maintaining this button pressed, you have to push the

second indicated button. Once confirmed the order, you could stop to press both buttons.

To program the memory, to select the scale or other specials operations allowed bythe circuit don't could be used at the same time than chronometer function. Before you have to stop and reset the chronometer.

ABOUT THE MDOULE. Each time you communicatean order to the CD-16, the State Led will quickly light and the acoustic indicator will emit a sound which could change according to the operationdone. More over, and to confirm that a button has been correctly pressed, when it is correctly done, the acoustic indicator will emit a short "bip" to

The relay Led will light when the relay is activated. The rest of Leds will light according to the operation done, as  $\mathbf{t}$  is indicated on the corresponding paragraph.

TIME SCALES. Once the module installation done, you could use it. Firstly you have to indicate the time scale. The minimum time to use thechronometer function is 0 sec. Nevertheless, as maximum time the CD-16 will offer two possibilities or two scale. The scale Nº1 allows a maximum time of 99 minutes and the scale Nº2 offersa maximum time of 99 hours. Originally the module is

Fig. 3. To select TimesCale.

supplied with the scale No1

To select the scale N°2, you have to press at the same time "#" and "8". If the operation has been correctly done, the Time Led will light. To select the scale N°1, you have to press at the same time "#" and "7". If the operation has been correctly done, the Time Led will be extinguished.

# + 7

# + 8

MANUAL / AUTOMATICCHRONOMETER FUNCTION. The CD-16 could be used on manual orautomatic mode The manual mode correspond to the normal operating mode of a chronometer with the beginning at zero and the end when you press "Stop". The automatic mode allows to program a time digit on the memory. From this digit you could start the chronometer function in count down and automatically stop when it reaches zero or a count up with an automatic stop when the programmed digit is reached.

To select an operating mode you have to proceed as following. If youprogram in memory any digit different of "0000" the CD-16 will operate on automatic mode with mentioned digit. At the opposite, you insert in memory "0000", the CD-16 will operate in manual mode.

To insert a digit in memory, you have to simultaneously press "#" and "3", immediately state and Chrono Leds will intermittently light to indicate that the program function is activated. Then, you have to introduce the wished digit. Each inserted digit will be indicated on the right side display, moving the others one position to the left side. When the display indicate the wished complete digit, press the confirmation button, "\*".

To reset the memory, you have to repeat the program process, recording the digit "0000". Each time you insert in the memory a new digit, to replace the previous one, it will be maintained into the memory even if you stop to supply the

If the inserted digit iscorrect, and stored in memory, the module will confirm theoperation with a continuous soun and lighting complete and momentarily Chrono and State Leds. If the digit is incorrect, the circuit will emit three acoustic sound and Chrono Led will intermittently light. Then, the program function will be abandoned without recording any digit. For instance, a wrong digit to memorise could be 10 min. 69sec., because the correct digit is 11

Note. The recorded digit in memory will correspond to minutes and seconds if you have selected the scale  $N^01$ , and hours and

Fig. 4. To programthememory + 3 + "DIGIT" + X

minutes if you have selected the scale N°2.

press at the same time "#" and "4", this one will intermittently appear on displayduring 5 sec. with an acoustic signal similar than a radio hour signal

TO VISUALISE MEMORY. If you don't remember the recorded digit or if you simply wish to see this digit, you have to . with an acoustic signalsimilar than a radio hour signal.

# + 4

CHRONOMETER UP/DOWN. You could configure the CD-16 to chronometer a count up or a count down. If you press at the same time "#" and "1" buttons, the Up/Down Led will light to indicate that you have selected tocount up. At the opposite, if you press at the same time "#" and "2" buttons, Up/Down Led will be extinguished toindicate that you have selected to count down.

With the count up, the chronometer function will start from zero. If you have programmed a digit in memory, the chronometer function will be stopped when the digit is reached. If you don't have

will be stopped when the digit is reached. If you don't have programmed any digit, when the chronometer reach the maximum digit (99,59), it will start again from zero. With the count down, the chronometer could onlybe used if you have previously programmed in memory a digit. Then, the chronometer will start the count down from this digit and stop when it reaches the zero. start the count down from this digit and stop when it reaches the zero

# + 1 Chronometer UP

**CHRONOMETER.** The basic functions of a chronometer as Start, Stop, Lapso or reset, are done as with watch. See Fig. 7, where the function of each button is described.

Start/Stop. To use the chronometer function, firstly you have to press the Start/stop function. To stop it you have to press again on this button. The Chrono Led will light when the chronometer function is

Fig. 7 . Toassign Chronometer Start/ Stop

Reset. When you stop the chronometer, the resultwill be visualised on the display. If you wish to erase this result, to placethe chronometer at zero, you have to reset it pressing the Lapso/Reset button

Lapso / Reset


Lapso. When the chronometer function is activated, before to press the Stop button, if you press the Lapso/Reset button, you will do a break allowing to read this time result, without internally stop the chronometer. When the

button, you will do a break allowing to fead this time fesult, without internally stop the Chronometer. When the "Lapsos" function is activated, the Chrono Led internitienthy light. To leave this function and go back to the internal count, you have to press again on the Lapso/Reset button.


If during the "Lapso" function you press the Start/Stop button, you will stop the chronometer's internal count. Then, when you press again the Laps/Reset button, it will be displayed the internal record where you have stoppedit, awaiting to a reset. (pressing again on the Lapso/Reset button).

IMPORTANT. Do not modify, amplify or remove the connection cable betweenkeyboard and CD-16 board. If you don't respect this point, the module doesn't properly work and the warranty will be automatically cancelled

## GENERAL WIRING MAP.



## DUTPUT CONNECTION. LOAD.



## TECHNICAL CONSULTATIONS.

ve any doubt, you could contact your wholesaler or our Technical Department.

sat@cebek.com | Fax. 34.93.432.29.95 | by mail. P.O. Box. 23455 - 08080 Barcelona - Spain.

Keep the invoice of this module. For any repair, the corresponding invoice had to be added. If the invoiceis not

ited together wish this module, the module's warranty will be automatically cancelled

All themodule's CEBEK have 3 years of total warranty in thecnical repairing, and spares from the date of buy





Much more CEBEK module's are aviable in our products range, please, require our general catalogue or visit our Webside