



cebek[®]



15 w. MONO POWER STAGE E-4

TECHNICAL CHARACTERISTICS

Voltage	24 V. D.C. (From 12 up to 35 V)
Minimum consumption	75 mA.
Maximum consumption	500 mA.
Minimum Input Signal	300 mV.
Maximum Input Signal	1,5 mV.
Output Impedance	4 - 8 W.
Frequencies Margin	30 - 18000 Hz.
15 W. Distorsion	2 %
R.M.S Power	15 W.
Musical Power	21 W.

Mono power stage specially indicated for small appliances. The maximum power is 15 w RNS at 4 ohms. Its main characteristic is based on the high quantity of appliance thanks to its reduce size and its quality. It includes protection against short-circuits, polarity inversion and connection terminals.

OPERATION

MODULE'S SUPPLYING. The E-4 module had to be supplied by correctly stabilised 24 V. D.C. power supply (from 12 up to 35 VDC), for this reason we suggest you to not use simple supply equipment neither rectifiers, which could negatively affect the module's operating , but a power supply.

We recommended you the FE-7 power supply which has been developed to perfectly answer to the circuit needs or a battery for mobile appliances. Install a fuse and a switch as it is required by teh "CE" regulation to offer a correct protection of the module as well as for your own safety. According to the drawing, you have to connect the positive, the negative and zero of the power supply to the corresponding terminals indicated in the schedule. The distance between power supply and module have to be as short as possible (15 cm as maximum.) Verify that the assembly has been correctly done.

To obtain a correct module's operating we suggest you to protect is against mains interference, to do that you have to place between the mains and the transformer .

OPERATING. See the paragraph "General wiring map". When the connections of the power supply are made, install a loudspeaker to the indicated terminal. The loudspeaker must to be 15 W (as minimum power).

Nevertheless, we suggest you to place a loudspeaker with 25 W. (as minimum power). If you use quality loudspeaker, you could highly appreciate the assembly.

INPUT SIGNAL. The input signal could be supplied by auxiliary devices as mixing desk, etc... but this input could not exceed 700 mV. Connect input terminals indicated in the schedule, and the distance between module (power stage) and its signal supply, has to be as short as possible. Use shielded cable for this assembly.

VOLUME CONTROL. To adjust the input signal level of the power stage, changing the volume, you have to install a 47 KW. logarithmic potentiometer. Use shielded cable for the installation (see the paragraph "General wiring map").

INSTALLATION. To install the power stage, we suggest you to fit it into a metallic box. This last has to be enough stronger to include module and its power supply and well ventilated. Indeed, during its operating the module will heat. Connect the negative terminal of the power stage to the ground of the box chassis. Then connect the also the ground to the chassis.

GENERAL WIRING MAP.

